

We Claim:

1. A method for maintaining an accurate channel estimate, the method comprising:
providing a reference channel estimate based on at least one first symbol;
generating a frequency domain representation of a second symbol including a plurality of pilots;
tracking phase change in the plurality of pilots of the second symbol relative to pilots of the at least one first symbol to produce correction factors; and
adjusting the reference channel estimate based upon the correction factors.
2. The method of claim 1, wherein tracking phase change includes determining for each pilot in the second symbol an associated total amount of rotation relative to a corresponding pilot in the at least one first symbol.
3. The method of claim 2, wherein tracking phase change includes determining a least squares fit based on the associated total amount of rotation for each pilot in the second symbol.
4. The method of claim 3 wherein tracking phase change includes generating, based on the least squares fit, second correction factors.
5. The method of claim 3, wherein tracking phase change includes
determining a slope and a phase intercept based upon the least squares fit, and
wherein generating, based on the least squares fit, includes generating the second correction factors based upon subcarrier numbers, the phase intercept, and the slope.
6. The method of claim 5, wherein generating the frequency domain representation of the second symbol includes sampling the second symbol early by a certain number of samples, further comprising:
determining an expected slope based on the certain number of samples by which the second symbol is sampled early; and
determining based on the slope and the expected slope a timing adjustment.

1 7. The method of claim 3, wherein tracking phase change includes
2 determining a slope and a phase intercept based upon the least squares fit,
3 determining a filtered slope and a filtered phase intercept based on the slope and the
4 phase intercept associated with the second symbol, and at least one other slope and at least one
5 other phase intercept associated with at least one symbol other than the second symbol, and
6 wherein generating, based on the least squares fit, includes generating the second
7 correction factors based upon subcarrier numbers, the filtered slope and the filtered phase
8 intercept.

1 8. The method of claim 7, further comprising:
2 determining a filtered phase intercept for a reference symbol, wherein the reference
3 symbol is separated from the second symbol by a certain number of symbols;
4 determining a residual frequency offset based upon the filtered phase intercept for the
5 reference symbol, the filtered phase intercept for the second symbol, and the certain number of
6 symbols.

1 9. The method of claim 8, wherein the reference symbol is a data symbol that is not
2 separated from the at least one first symbol by any other data symbol.

1 10. The method of claim 8, wherein the reference symbol is the one of the at least one first
2 symbol.

1 11. The method of claim 1, the method comprising:
2 producing, for each pilot in the second symbol whose magnitude is above a threshold, an
3 associated total amount of rotation relative to a corresponding pilot in the at least one first
4 symbol;
5 producing for one of the pilots in the second symbol total amount of rotation based on the
6 associated total amount of rotation of other pilots in the second symbol;
7 determining a least squares fit based on the associated total amount of rotation for each
8 pilot in the second symbol whose magnitude is above the threshold and the total amount of
9 rotation based on the associated total amount of rotation of other pilots in the second symbol; and

10 generating, based on the least squares fit, the plurality of second correction factors.

1 12. The method of claim 11, wherein producing for one of the pilots includes producing for
2 one of the pilots in the second symbol whose magnitude is below the threshold a total amount of
3 rotation based on the associated total amount of rotation of other pilots in the second symbol.

1 13. A method for maintaining an accurate channel estimate, the method comprising:
2 providing a reference channel estimate based on at least one training training symbol;
3 generating a frequency domain representation of a first data symbol including a plurality
4 of pilots;
5 tracking phase change in the plurality of pilots of the first data symbol relative to pilots of
6 the at least one training training symbol to produce first correction factors; and
7 adjusting the reference channel estimate based upon the first correction factors.

1 14. The method of claim 13, wherein tracking phase change includes determining for each
2 pilot in the first data symbol an associated total amount of rotation relative to a corresponding
3 pilot in the at least one training symbol.

1 15. The method of claim 14, wherein tracking phase change includes determining a least
2 squares fit based on the associated total amount of rotation for each pilot in the first data symbol.

1 16. The method of claim 15, wherein tracking phase change includes generating, based on
2 the least squares fit, second correction factors.

1 17. The method of claim 15, wherein tracking phase change includes
2 determining a slope and a phase intercept based upon the least squares fit, and
3 wherein generating, based on the least squares fit, includes generating the second
4 correction factors based upon subcarrier numbers, the phase intercept, and the slope.

1 18. The method of claim 17, wherein generating the frequency domain representation of the
2 first data symbol includes sampling the first data symbol early by a certain number of samples,
3 further comprising:

4 determining an expected slope based on the certain number of samples by which the first
5 data symbol is sampled early; and
6 determining based on the slope and the expected slope a timing adjustment.

1 19. The method of claim 15, wherein tracking phase change includes
2 determining a slope and a phase intercept based upon the least squares fit,
3 determining a filtered slope and a filtered phase intercept based on the slope, the phase
4 intercept, and at least one other slope and at least one other phase intercept associated with at
5 least one symbol other than the first data symbol, and

6 wherein generating, based on the least squares fit, includes generating the second
correction factors based upon subcarrier numbers, the filtered slope and the filtered phase
intercept.

1 20. The method of claim 19, further comprising:
2 determining a filtered phase intercept for a reference symbol, wherein the reference
3 symbol is separated from the first data symbol by a certain number of symbols;
4 determining a residual frequency offset based upon the filtered phase intercept for the
5 reference symbol, the filtered phase intercept for the first data symbol, and the certain number of
6 symbols.

1 21. The method of claim 20, wherein the reference symbol is a data symbol that is not
2 separated from the at least one training symbol by any other data symbol.

1 22. The method of claim 20, wherein the reference symbol is one of the at least one training
2 symbol.

1 23. The method of claim 13, the method comprising:
2 producing, for each pilot in the first data symbol whose magnitude is above a threshold,

3 an associated total amount of rotation relative to a corresponding pilot in the at least one training
4 training symbol;
5 producing for one of the pilots in the first data symbol a total amount of rotation based on
6 the associated total amount of rotation of other pilots in the first data symbol;
7 determining a least squares fit based on the associated total amount of rotation for each
8 pilot in the first data symbol whose magnitude is above the threshold and the total amount of
9 rotation based on the associated total amount of rotation of other pilots in the first data symbol;
10 and
11 generating, based on the least squares fit, the plurality of second correction factors.

1 24. The method of claim 23, wherein producing for one of the pilots includes producing for
2 one of the pilots in the first data symbol whose magnitude is below the threshold a total amount
3 of rotation based on the associated total amount of rotation of other pilots in the first data
4 symbol.

1 25. A method for maintaining an accurate channel estimate, the method comprising:
2 generating a frequency domain representation of at least one training training symbol;
3 determining a number of clock cycles that the at least one training symbol is sampled
4 early;
5 generating first correction factors based on the number of clock cycles;
6 adjusting the frequency domain representation based upon the first correction factors to
7 produce a reference channel estimate;
8 generating a frequency domain representation of a first data symbol;
9 tracking phase change in pilots of the first data symbol relative to pilots of the at least one
10 training symbol to produce second correction factors; and
11 adjusting the reference channel estimate based upon the second correction factors.

1 26. The method of claim 25, wherein adjusting results in pilot signals in the frequency
2 domain representation of the at least one training symbol having a substantially flat phase
3 response.

1 27. The method of claim 25, wherein tracking phase change includes determining for each
2 pilot in the first data symbol an associated total amount of rotation relative to a corresponding
3 pilot in the at least one training symbol.

1 28. The method of claim 27, wherein tracking phase change includes determining a least
2 squares fit based on the associated total amount of rotation for each pilot.

1 29. The method of claim 28, wherein tracking phase change includes generating, based on
2 the least squares fit, the second correction factors.

1 30. The method of claim 28, wherein tracking phase change includes
2 determining a slope and a phase intercept based upon the least squares fit, and
3 wherein generating, based on the least squares fit, includes generating the second
4 correction factors based upon subcarrier numbers, the phase intercept, and the slope.

1 31. The method of claim 30, wherein generating the frequency domain representation of the
2 first data symbol includes sampling the first data symbol early by a certain number of samples,
3 further comprising:

4 determining an expected slope based on the certain number of samples by which the first
5 data symbol is sampled early; and
6 determining based on the slope and the expected slope a timing adjustment.

1 32. The method of claim 28, wherein tracking phase change includes
2 determining a slope and a phase intercept based upon the least squares fit,
3 determining a filtered slope and a filtered phase intercept based on the slope, the phase
4 intercept, and previous slopes and previous phase intercepts associated with data symbols that
5 arrived before the first data symbol, and
6 wherein generating, based on the least squares fit, includes generating the second
7 correction factors based upon subcarrier numbers, the filtered slope and the filtered phase
8 intercept.

1 33. The method of claim 32, further comprising:
2 determining a filtered phase intercept for a reference symbol, wherein the reference
3 symbol is separated from the first data symbol by a certain number of symbols;
4 determining a residual frequency offset based upon the filtered phase intercept for the
5 reference symbol, the filtered phase intercept for the first data symbol, and the certain number of
6 symbols.

1 34. The method of claim 33, wherein the reference symbol is a data symbol that is not
2 separated from the at least one training symbol by any other data symbol.

1 35. The method of claim 33, wherein the reference symbol is the one of the at least one
2 training symbol.

1 36. The method of claim 25, the method comprising:
2 producing, for each pilot in the first data symbol whose magnitude is above a threshold,
3 an associated total amount of rotation relative to a corresponding pilot in the at least one training
4 symbol;
5 producing for one of the pilots in the first data symbol a total amount of rotation based on
6 the associated total amount of rotation of other pilots in the first data symbol;
7 determining a least squares fit based on the associated total amount of rotation for each
8 pilot in the first data symbol whose magnitude is above the threshold and the total amount of
9 rotation based on the associated total amount of rotation of other pilots in the first data symbol;
10 and
11 generating, based on the least squares fit, the plurality of second correction factors.

1 37. A method for maintaining an accurate channel estimate, the method comprising:
2 generating a frequency domain representation of at least one training symbol;
3 determining number of clock cycles that the at least one training symbol is sampled early;
4 generating a plurality of first correction factors based on the number of clock cycles;
5 wherein adjusting results in pilot signals in the frequency domain representation of the at
6 least one training symbol having a substantially flat phase response

7 adjusting the frequency domain representation based upon the plurality of first correction
8 factors to produce a reference channel estimate;
9 generating a frequency domain representation of a first data symbol;
10 tracking phase change in pilots of the first data symbol relative to the at least one training
11 symbol to produce second correction factors;
12 wherein tracking phase change includes determining for each pilot in the first data
13 symbol an associated total amount of rotation relative to a corresponding pilot in the at least one
14 training symbol, determining a least squares fit based on the associated total amount of rotation
15 for each pilot, and generating, based on the least squares fit, the second correction factors; and
16 adjusting the reference channel estimate based upon the second correction factors.

1 38. A method for maintaining an accurate channel estimate, the method comprising:
2 generating a frequency domain representation of at least one training symbol;
3 determining number of clock cycles that the at least one training symbol is sampled early;
4 generating a plurality of first correction factors based on the number of clock cycles;
5 wherein adjusting results in pilot signals in the frequency domain representation of the at
6 least one training symbol having a substantially flat phase response
7 adjusting the frequency domain representation based upon the first correction factors to
8 produce a reference channel estimate;
9 generating a frequency domain representation of a first data symbol;
10 tracking phase change in pilots of the first data symbol relative to pilots in the at least one
11 training symbol to produce second correction factors;
12 wherein tracking phase change includes determining for each pilot in the first data
13 symbol an associated total amount of rotation relative to a corresponding pilot in the at least one
14 training symbol, determining a least squares fit based on the associated total amount of rotation
15 for each pilot, generating, based on the least squares fit, the second correction factors,
16 determining a slope and phase intercept based upon the least squares fit, and wherein generating,
17 based on the least squares fit, includes generating the second correction factors based upon
18 subcarrier numbers, the phase intercept, and the slope; and
19 adjusting the reference channel estimate based upon the second correction factors.

1 39. An apparatus for maintaining an accurate channel estimate, the apparatus comprising:
2 a frequency domain transform unit that is to generate a frequency domain representation
3 of at least one training symbol and a frequency domain representation of a first data symbol;
4 an early sampling detection circuit that is to determine, based on the frequency domain
5 representation of the at least one training symbol, number of clock cycles that the at least one
6 training symbol is sampled early;
7 an angle-to-vector converter that is to produce a plurality of first correction factors based
8 on the number of clock cycles;
9 a first multiplier that is to adjust the frequency domain representation based upon the first
10 correction factors to produce a reference channel estimate;
11 a pilot phase tracking circuit that is to track total phase rotation in pilots of the first data
12 symbol relative to pilots in the at least one training symbol to produce a plurality of second
13 correction factors; and
14 a second multiplier that is to adjust the reference channel estimate based upon the
15 plurality of second correction factors.

1 40. The apparatus of claim 39, wherein the pilot phase tracking circuit is to determine for
2 each pilot in the first data symbol an associated total amount of rotation relative to a
3 corresponding pilot in the at least one training symbol.

1 41. The apparatus of claim 39, wherein pilot signals in the reference channel estimate have a
2 substantially flat phase response.

1 42. The apparatus of claim 41, wherein the pilot phase tracking circuit is to determine a least
2 squares fit based on the associated total amount of rotation for each pilot.

1 43. The apparatus of claim 42 wherein the pilot phase tracking circuit generates, based on the
2 least squares fit, the plurality of second correction factors.

1 44. The apparatus of claim 43, wherein the pilot phase tracking circuit determines a slope and

2 a phase intercept based upon the least squares fit, and generates the plurality of second correction
3 factors based upon subcarrier numbers, the phase intercept, and the slope.

1 45. The apparatus of claim 44, wherein the frequency domain representation of the first data
2 symbol is based on sampling the first data symbol early by a certain number of samples, and
3 wherein the pilot phase tracking circuit determines an expected slope based on the certain
4 number of samples by which the first data symbol is sampled early, and determines based on the
5 slope and the expected slope a timing adjustment.

1 46. The apparatus of claim 42, wherein the pilot phase tracking circuit determines a slope and
2 a phase intercept based upon the least squares fit, determines a filtered slope and a filtered phase
3 intercept based on the slope, the phase intercept, and previous slopes and previous phase
4 intercepts associated with data symbols that arrived before the first data symbol, and generates
5 the plurality of second correction factors based upon subcarrier numbers, the filtered slope and
6 the filtered phase intercept.

1 47. The apparatus of claim 46 wherein the pilot phase tracking circuit determines a filtered
2 phase intercept for a reference symbol, wherein the reference symbol is separated from the first
3 data symbol by a certain number of symbols and determines a residual frequency offset based
4 upon the filtered phase intercept of the reference symbol, the filtered phase intercept of the first
5 data symbol, and the certain number of symbols.

1 48. The apparatus of claim 47, wherein the reference symbol is a data symbol that is not
2 separated from the at least one training symbol by any other data symbol.

1 49. The apparatus of claim 47, wherein the reference symbol is the one of the at least one
2 training symbol.

1 50. The apparatus of claim 42, wherein the pilot phase tracking circuit is to produce, for each
2 pilot in the first data symbol whose magnitude is above a threshold, an associated total amount of
3 rotation relative to a corresponding pilot in the at least one training symbol, produce for one of

the pilots in the first data symbol a total amount of rotation based on the associated total amount of rotation of other pilots in the first data symbol, determine a least squares fit based on the associated total amount of rotation for each pilot in the first data symbol whose magnitude is above the threshold and the total amount of rotation based on the associated total amount of rotation of other pilots in the first data symbol, and generate, based on the least squares fit, the plurality of second correction factors.

51. An apparatus for maintaining an accurate channel estimate, the apparatus comprising:
a frequency domain transform unit that is to generate a frequency domain representation of at least one training symbol and a frequency domain representation of a first data symbol;
an early sampling detection circuit that is to determine, based on the frequency domain representation of the at least one training symbol, number of clock cycles that the at least one training symbol is sampled early;
an angle-to-vector converter that is to produce a plurality of first correction factors based on the number of clock cycles;
a first multiplier that is to adjust the frequency domain representation based upon the first correction factors to produce a reference channel estimate;
a pilot phase tracking circuit that is to determine for each pilot in the first data symbol an associated total amount of rotation relative to a corresponding pilot in the at least one training symbol, is to determine a least squares fit based on the associated total amount of rotation for each pilot, and is to produce a plurality of second correction factors; and
a second multiplier that is to adjust the reference channel estimate based upon the plurality of second correction factors.

52. An apparatus for maintaining an accurate reference channel estimate, the apparatus comprising:
a memory that stores the reference channel estimate;
a pilot phase tracking circuit that is receive pilots of at least one training symbol and pilots of a first data symbol and is to determine for a plurality of the pilots in the first data symbol an associated total amount of rotation relative to a corresponding pilot in the at least one training symbol, is to determine a least squares fit based on the associated total amount of

8 rotation for each pilot of the plurality of the pilots in the first data symbol, and is to produce a
9 plurality of first correction factors based on the least squares fit; and
10 a second multiplier that is to adjust the reference channel estimate based upon the
11 plurality of first correction factors.

1 53. The apparatus of claim 52, wherein the pilot phase tracking circuit determines a slope and
2 a phase intercept based upon the least squares fit, and generates a plurality of second correction
3 factors based upon subcarrier numbers, the phase intercept, and the slope.

1 54. The apparatus of claim 53, wherein the first data symbol has a first data symbol
2 frequency representation that is based on sampling the first data symbol early by a certain
3 number of samples, and wherein the pilot phase tracking circuit determines an expected slope
4 based on the certain number of samples by which the first data symbol is sampled early, and
5 determines based on the slope and the expected slope a timing adjustment.

1 55. The apparatus of claim 52, wherein the pilot phase tracking circuit determines a slope and
2 a phase intercept based upon the least squares fit, determines a filtered slope and a filtered phase
3 intercept based on the slope, the phase intercept, and previous slopes and previous phase
4 intercepts associated with data symbols that arrived before the first data symbol, and generates
5 the plurality of second correction factors based upon subcarrier numbers, the filtered slope and
6 the filtered phase intercept.

1 56. The apparatus of claim 55 wherein the pilot phase tracking circuit determines a filtered
2 phase intercept for a reference symbol, wherein the reference symbol is separated from the first
3 data symbol by a certain number of symbols and determines a residual frequency offset based
4 upon the filtered phase intercept of the reference symbol, the filtered phase intercept of the first
5 data symbol, and the certain number of symbols.

1 57. The apparatus of claim 56, wherein the reference symbol is a data symbol that is not
2 separated from the at least one training symbol by any other data symbol.

1 58. The apparatus of claim 56, wherein the reference symbol is the one of the at least one
2 training symbol.

1 59. The apparatus of claim 52, wherein the pilot phase tracking circuit is to produce, for a
2 plurality of pilots in the first data symbol whose magnitude is above a threshold, an associated
3 total amount of rotation relative to a corresponding pilot in the at least one symbol, produce for
4 one of the pilots in the first data symbol a total amount of rotation based on the associated total
5 amount of rotation of other pilots in the first data symbol, determine a least squares fit based on
6 the associated total amount of rotation for each pilot in the first data symbol whose magnitude is
7 above the threshold and the total amount of rotation based on the associated total amount of
8 rotation of other pilots in the first data symbol, and generate, based on the least squares fit, the
9 plurality of second correction factors.

100
200
300
400
500
600
700
800
900
1000
1100
1200
1300
1400
1500
1600
1700
1800
1900
2000
2100
2200
2300
2400
2500
2600
2700
2800
2900
3000
3100
3200
3300
3400
3500
3600
3700
3800
3900
4000
4100
4200
4300
4400
4500
4600
4700
4800
4900
5000
5100
5200
5300
5400
5500
5600
5700
5800
5900
6000
6100
6200
6300
6400
6500
6600
6700
6800
6900
7000
7100
7200
7300
7400
7500
7600
7700
7800
7900
8000
8100
8200
8300
8400
8500
8600
8700
8800
8900
9000
9100
9200
9300
9400
9500
9600
9700
9800
9900
10000
10100
10200
10300
10400
10500
10600
10700
10800
10900
11000
11100
11200
11300
11400
11500
11600
11700
11800
11900
12000
12100
12200
12300
12400
12500
12600
12700
12800
12900
13000
13100
13200
13300
13400
13500
13600
13700
13800
13900
14000
14100
14200
14300
14400
14500
14600
14700
14800
14900
15000
15100
15200
15300
15400
15500
15600
15700
15800
15900
16000
16100
16200
16300
16400
16500
16600
16700
16800
16900
17000
17100
17200
17300
17400
17500
17600
17700
17800
17900
18000
18100
18200
18300
18400
18500
18600
18700
18800
18900
19000
19100
19200
19300
19400
19500
19600
19700
19800
19900
20000
20100
20200
20300
20400
20500
20600
20700
20800
20900
21000
21100
21200
21300
21400
21500
21600
21700
21800
21900
22000
22100
22200
22300
22400
22500
22600
22700
22800
22900
23000
23100
23200
23300
23400
23500
23600
23700
23800
23900
24000
24100
24200
24300
24400
24500
24600
24700
24800
24900
25000
25100
25200
25300
25400
25500
25600
25700
25800
25900
26000
26100
26200
26300
26400
26500
26600
26700
26800
26900
27000
27100
27200
27300
27400
27500
27600
27700
27800
27900
28000
28100
28200
28300
28400
28500
28600
28700
28800
28900
29000
29100
29200
29300
29400
29500
29600
29700
29800
29900
30000
30100
30200
30300
30400
30500
30600
30700
30800
30900
31000
31100
31200
31300
31400
31500
31600
31700
31800
31900
32000
32100
32200
32300
32400
32500
32600
32700
32800
32900
33000
33100
33200
33300
33400
33500
33600
33700
33800
33900
34000
34100
34200
34300
34400
34500
34600
34700
34800
34900
35000
35100
35200
35300
35400
35500
35600
35700
35800
35900
36000
36100
36200
36300
36400
36500
36600
36700
36800
36900
37000
37100
37200
37300
37400
37500
37600
37700
37800
37900
38000
38100
38200
38300
38400
38500
38600
38700
38800
38900
39000
39100
39200
39300
39400
39500
39600
39700
39800
39900
40000
40100
40200
40300
40400
40500
40600
40700
40800
40900
41000
41100
41200
41300
41400
41500
41600
41700
41800
41900
42000
42100
42200
42300
42400
42500
42600
42700
42800
42900
43000
43100
43200
43300
43400
43500
43600
43700
43800
43900
44000
44100
44200
44300
44400
44500
44600
44700
44800
44900
45000
45100
45200
45300
45400
45500
45600
45700
45800
45900
46000
46100
46200
46300
46400
46500
46600
46700
46800
46900
47000
47100
47200
47300
47400
47500
47600
47700
47800
47900
48000
48100
48200
48300
48400
48500
48600
48700
48800
48900
49000
49100
49200
49300
49400
49500
49600
49700
49800
49900
50000
50100
50200
50300
50400
50500
50600
50700
50800
50900
51000
51100
51200
51300
51400
51500
51600
51700
51800
51900
52000
52100
52200
52300
52400
52500
52600
52700
52800
52900
53000
53100
53200
53300
53400
53500
53600
53700
53800
53900
54000
54100
54200
54300
54400
54500
54600
54700
54800
54900
55000
55100
55200
55300
55400
55500
55600
55700
55800
55900
56000
56100
56200
56300
56400
56500
56600
56700
56800
56900
57000
57100
57200
57300
57400
57500
57600
57700
57800
57900
58000
58100
58200
58300
58400
58500
58600
58700
58800
58900
59000
59100
59200
59300
59400
59500
59600
59700
59800
59900
60000
60100
60200
60300
60400
60500
60600
60700
60800
60900
61000
61100
61200
61300
61400
61500
61600
61700
61800
61900
62000
62100
62200
62300
62400
62500
62600
62700
62800
62900
63000
63100
63200
63300
63400
63500
63600
63700
63800
63900
64000
64100
64200
64300
64400
64500
64600
64700
64800
64900
65000
65100
65200
65300
65400
65500
65600
65700
65800
65900
66000
66100
66200
66300
66400
66500
66600
66700
66800
66900
67000
67100
67200
67300
67400
67500
67600
67700
67800
67900
68000
68100
68200
68300
68400
68500
68600
68700
68800
68900
69000
69100
69200
69300
69400
69500
69600
69700
69800
69900
70000
70100
70200
70300
70400
70500
70600
70700
70800
70900
71000
71100
71200
71300
71400
71500
71600
71700
71800
71900
72000
72100
72200
72300
72400
72500
72600
72700
72800
72900
73000
73100
73200
73300
73400
73500
73600
73700
73800
73900
74000
74100
74200
74300
74400
74500
74600
74700
74800
74900
75000
75100
75200
75300
75400
75500
75600
75700
75800
75900
76000
76100
76200
76300
76400
76500
76600
76700
76800
76900
77000
77100
77200
77300
77400
77500
77600
77700
77800
77900
78000
78100
78200
78300
78400
78500
78600
78700
78800
78900
79000
79100
79200
79300
79400
79500
79600
79700
79800
79900
80000
80100
80200
80300
80400
80500
80600
80700
80800
80900
81000
81100
81200
81300
81400
81500
81600
81700
81800
81900
82000
82100
82200
82300
82400
82500
82600
82700
82800
82900
83000
83100
83200
83300
83400
83500
83600
83700
83800
83900
84000
84100
84200
84300
84400
84500
84600
84700
84800
84900
85000
85100
85200
85300
85400
85500
85600
85700
85800
85900
86000
86100
86200
86300
86400
86500
86600
86700
86800
86900
87000
87100
87200
87300
87400
87500
87600
87700
87800
87900
88000
88100
88200
88300
88400
88500
88600
88700
88800
88900
89000
89100
89200
89300
89400
89500
89600
89700
89800
89900
90000
90100
90200
90300
90400
90500
90600
90700
90800
90900
91000
91100
91200
91300
91400
91500
91600
91700
91800
91900
92000
92100
92200
92300
92400
92500
92600
92700
92800
92900
93000
93100
93200
93300
93400
93500
93600
93700
93800
93900
94000
94100
94200
94300
94400
94500
94600
94700
94800
94900
95000
95100
95200
95300
95400
95500
95600
95700
95800
95900
96000
96100
96200
96300
96400
96500
96600
96700
96800
96900
97000
97100
97200
97300
97400
97500
97600
97700
97800
97900
98000
98100
98200
98300
98400
98500
98600
98700
98800
98900
99000
99100
99200
99300
99400
99500
99600
99700
99800
99900
100000
100100
100200
100300
100400
100500
100600
100700
100800
100900
101000
101100
101200
101300
101400
101500
101600
101700
101800
101900
102000
102100
102200
102300
102400
102500
102600
102700
102800
102900
103000
103100
103200
103300
103400
103500
103600
103700
103800
103900
104000
104100
104200
104300
104400
104500
104600
104700
104800
104900
105000
105100
105200
105300
105400
105500
105600
105700
105800
105900
106000
106100
106200
106300
106400
106500
106600
106700
106800
106900
107000
107100
107200
107300
107400
107500
107600
107700
107800
107900
108000
108100
108200
108300
108400
108500
108600
108700
108800
108900
109000
109100
109200
109300
109400
109500
109600
109700
109800
109900
110000
110100
110200
110300
110400
110500
110600
110700
110800
110900
111000
111100
111200
111300
111400
111500
111600
111700
111800
111900
112000
112100
112200
112300
112400
112500
112600
112700
112800
112900
113000
113100
113200
113300
113400
113500
113600
113700
113800
113900
114000
114100
114200
114300
114400
114500
114600
114700
114800
114900
115000
115100
115200
115300
115400
115500
115600
115700
115800
115900
116000
116100
116200
116300
116400
116500
116600
116700
116800
116900
117000
117100
117200
117300
117400
117500
117600
117700
117800
117900
118000
118100
118200
118300
118400
118500
118600
118700
118800
118900
119000
119100
119200
119300
119400
119500
119600
119700
119800
119900
120000
120100
120200
120300
120400
120500
120600
120700
120800
120900
121000
121100
121200
121300
121400
121500
121600
121700
121800
121900
122000
122100
122200
122300
122400
122500
122600
122700
122800
122900
123000
123100
123200
123300
123400
123500
123600
123700
123800
123900
124000
124100
124200
124300
124400
124500
124600
124700
124800
124900
125000
125100
125200
125300
125400
125500
125600
125700
125800
125900
126000
126100
126200
126300
126400
126500
126600
126700
126800
126900
127000
127100
127200
127300
127400
127500
127600
127700
127800
127900
128000
128100
128200
128300
128400
128500
128600
128700
128800
128900
129000
129100
129200
129300
129400
129500
129600
129700
129800
129900
130000
130100
130200
130300
130400
130500
130600
130700
130800
130900
131000
131100
131200
131300
131400
131500
131600
131700
131800
131900
132000
132100
132200
132300
132400
132500
132600
132700
132800
132900
133000
133100
133200
133300
133400
133500
133600
133700
133800
133900
134000
134100
134200
134300
134400
134500
134600
134700
134800
134900
135000
135100
135200
135300
135400
135500
135600
135700
135800
135900
136000
136100
136200
136300
136400
136500
136600
136700
136800
136900
137000
137100
137200
137300
137400
137500
137600
137700
137800
137900
138000
138100
138200
138300
138400
138500
138600
138700
138800
138900
139000
139100
139200
139300
139400
139500
139600
139700
139800
139900
140000
140100
140200
140300
140400
140500
140600
140700
140800
140900
141000
141100
141200
141300
141400
141500
141600
141700
141800
141900
142000
142100
142200
142300
142400
142500
142600
142700
142800
142900
143000
143100
143200
143300
143400
143500
143600
143700
143800
143900
144000
144100
144200
144300
144400
144500
144600
144700
144800
144900
145000
145100
145200
145300
145400
145500
145600
145700
145800
145900
146000
146100
146200
146300
146400
146500
146600
146700
146800
146900
147000
147100
147200
147300
147400
147500
147600
147700
147800
147900
148000
148100
148200
148300
148400
148500
148600
148700
148800
148900
149000
149100
149200
149300
149400
149500
149600
149700
149800
149900
150000
150100
150200
150300
150400
150500
150600
150700
150800
150900
151000
151100
151200
151300
151400
151500
151600
151700
151800
151900
152000
152100
152200
152300
152400
152500
152600
152700
152800
152900
153000
153100
153200
153300
153400
153500
153600
153700
153800
153900
154000
154100
154200
154300
154400
154500
154600
154700
154800
154900
155000
155100
155200
155300
155400
155500
155600
155700
155800
155900
156000
156100
156200
156300
156400
156500
156600
156700
156800
156900
157000
157100
157200
157300
157400
157500
157600
157700
157800
157900
158000
158100
158200
158300
158400
158500
158600
158700
158800
158900
159000
159100
159200
159300
159400
159500
159600
159700
159800
159900
160000
160100
160200
160300
160400
160500
160600
160700
160800
160900
161000
161100
161200
161300
161400
161500
161600
161700
161800
161900
162000
162100
162200
162300
162400
162500
162600
162700
162800
162900
163000
163100
163200
163300
163400
163500
163600
163700
163800
163900
164000
164100
164200
164300
164400
164500
164600
164700
164800
164900

6 a multiply unit that is to scale the reference channel estimate based upon the scaling
7 factor.

1 63. The apparatus of claim 62, wherein the magnitude tracking circuit is to filter the data
2 symbol power to produce a filtered data symbol power and is to calculate the scaling factor based
3 upon the filtered data symbol power.

2014-03-20 10:04:00